

Compact HE 1U power systems

Increasing network speed demands flexible and expandable DC power solutions. Due to its small size, high efficiency, reliability and wide range of communication, the Flatpack S System is the key for future needs. The shallow depth makes the system suitable for most cabinets and thereby excellent as a replacement unit.



FLATPACK S 1U SYSTEMS

1U x 19" 48V – 2R/3R

Doc CTOS0X01.DS3 – v6

APPLICATIONS

TELECOM – MOBILE / WIRELESS

- RADIO BASE STATIONS / CELL SITES
- LTE / 4G / WIMAX
- DISTRIBUTED ANTENNA SYSTEMS
- MICROWAVE
- BROADBAND

TELECOM – FIXED

- TELEPHONY SERVERS / SWITCHES
- FIBER OPTICS / FTTX
- MICROWAVE
- CABLE
- BROADBAND



SMARTPACK S CONTROLLER



FLATPACK S 48V 1800W RECTIFIER

KEY FEATURES

- COMPLETE SYSTEM
 - 0 SMARTPACK S CONTROLLER
 - 0 RECTIFIERS
 - 0 BATTERY DISTRIBUTION
 - 0 LOAD DISTRIBUTION
- 262 MM SYSTEM DEPTH
- 1U HEIGHT
- HOT PLUGGABLE RECTIFIERS
- HOT PLUGGABLE CONTROLLER
- ADVANCED CONTROL AND MONITORING THROUGH ETHERNET PORT
- 2R (40A) LOAD OPTIONS
 - 0 7 X 30A MCB DRAWER (OPTIONAL LVLD)
 - 0 4 X 30A MCB FRONT
 - 0 7 X 15A FUSE FRONT
- 3R (100A) LOAD OPTIONS
 - 0 2 X 80A

FLATPACK S 1U SYSTEMS

1U X 19" 48V – 2R/3R

Model	1 Controller + 2 Rectifiers	1 Controller + 3 Rectifiers
Part number	CTOS0201.xxx	CTOS0301.xxx
INPUT DATA		
Voltage	100 - 250V _{AC}	100 - 250V _{AC}
Mains Configuration	230V _{AC} , 1 phase or 2 x 1phase	230V _{AC} , 3 x 1 phase or 3 phase(Δ) 230/400V _{AC} , 3 phase (Y)
Mains Connection	2,5mm ² Terminal blocks, rear connection	
Frequency	45 to 66Hz	
OUTPUT DATA		
Voltage	- 48Vdc	- 48Vdc
Max. Current	40A	100A
BATTERY DISTRIBUTION		
LVBD	Default	Default
Breaker (Plug-in type) maximum size	2 x 40A ¹⁾	2 x 80A ¹⁾
Connection (rear)	16mm ² Terminal blocks	M6 cable lug
LOAD DISTRIBUTION		
Rear connections	N/A	2 x 80A, M6 cable lug
Rear cabel entry, front access Connections, screw terminals Optional LVLD	7 x 30A MCB ²⁾ 7 X 4mm ² on MCB 1 and 2	N/A
Front connections Plug-able screw terminals	4 x 30A MCB / 7 x 15A Fuse 4mm ²	N/A
CONTROL & MONITORING		
Smartpack S	6x Input/Output and Ethernet, See Smartpack S datasheet	
MECHANICAL DATA		
Dimensions (W/H/D)	19"/1U/262mm Recommended minimum cabinet depth, 300 mm	
Weight, including controller and distributions, excluding rectifiers	5.3 kg [11.7 lbs]	5.2 kg [11.5 lbs]
DESIGN STANDARDS		
Electrical safety	UL 60950-1, EN 60950-1	
EMC	ETSI EN 300 386 V.1.4.1 EN 61000-6-1 (immunity, light industry) EN 61000-6-2 (immunity, industry) EN 61000-6-3 (emission, light industry) EN 61000-6-4 (emission, industry)	
Environment	ETSI EN 300 019-2-1 Class 1.2 ETSI EN 300 019-2-2 Class 2.3 ETSI EN 300 019-2-3 Class 3.2	

1) If only one string is used, one of the battery breakers can be configured as a load breaker.

2) Drawer solution, front access for actual connection, but cables enters from rear

1) If only one string is used, one of the battery breakers can be configured as a load breaker.

2) Drawer solution, front access for actual connection, but cables enters from rear